VW EDC15 IMMO EMULATOR

White diode – power

Blue diode – after adjusting it lights constantly and blinks every other second

In Universal Julie emulator solder jumper *J2*

White diode – power

Blue diode – after adjusting it lights constantly and blinks every other second

In Universal Julie emulator solder jumpers *J1 and J2*

SOLD AS UNIVERSAL *JULIE* EMULATOR

**VW EDC15 immo OFF or ON programs
are a single use and they can only be used in one car!**

technical support at www.carlabimmo.com/forumang/

VW EDC15 immo emulator – W2 and W3 systems, diesel engines from 2000 to 2004, some to 2006, and even 2008 (except Audi with coded pump)

Program selection is effected by proper soldering of jumpers

Suitable for vehicles with 2-socket ECUs

Engine capacity

1.2 TDI   1.4 TDI   1.9 TDI   2.5 TDI

This emulator replaces damaged immobiliser, instrument cluster or a car key

Immo gets removed once the emulator is connected to the OBD socket

In the case of losing car keys or car theft,you will be able to drive to the nearest car garage

GND   blue
+12V ACC   red
K line   green

Before using the emulator, check if there is a connection between ECU and OBD2

You can use a VW EDC15 emulator in the following situations

technical support at www.carlabimmo.com/forumang/

When getting an Engine Control Module Blocked by Immobiliser fault when making connection with ECU with a diagnostic interface or if your car starts and then dies

16-pin OBD2 socket

1. Disconnect plug with wires from Julie emulator

2. Select program by soldering jumpers

3. Connect wires to the OBD2 socket

4. TURN IGNITION

5. When the ignition is turned, connect the emulator plug to the emulator PCB.
Blue LED flashes fast and after several seconds the LED should light constantly and
blink every other second

6. Turn ignition OFF and disconnect emulator

**VW EDC15 immo OFF or ON programs
are a single use and they can only be used in one car!**

**VW EDC15 emulator does not remove immo due to a program change
to flash memory in ECU:**

EDC15 Audi A6 2.5 TDI V6 2003
8E0 907 401 M   0 281 011 255

14-pin socket in LT

Fitting procedure of emulator is the same as for the OBD2 socket

Warning!!!

Due to possible construction changes of cars, check signals with multimeter in the ECU plug.

www.carlabimmo.com

Last updated 05.09.2014